

INSTALLATION INSTRUCTION
Line Chandelier - dwelLED™
PD-51148

WAC LIGHTING
Responsible Lighting®

WARNING

IMPORTANT: NEVER attempt any work without shutting off the electricity.

- Read all instructions before installing.
- System is intended for installation by a qualified electrician in accordance with the National Electrical Code and local regulations.
- Go to the main fuse box, or circuit breaker. Place the main power switch in the "OFF" position and unscrew the fuse(s) or switch "OFF" the circuit breaker switch(es) that control the power to the fixture or room that you are working on.
- Place the wall switch in the "OFF" position.

CAUTION

- All parts must be used as indicated in these instructions. Do not substitute any parts, leave parts out, or use any parts that are worn out or broken. Failure to follow this instruction could invalidate the ETL/CETL listing of this fixture.
- CAUTION When handling the fixture, do not apply pressure to the LEDs. Hold the fixture by the base only.

AVERTISSEMENT

IMPORTANT : Coupez l'électricité avant TOUTE manipulation.

- Lisez toutes les instructions avant d'installer.
- Système est destiné à être installé par un électricien qualifié en conformité avec le code national de l'électricité et les règlements locaux.
- Accédez au panneau central de disjoncteurs ou de fusibles de votre demeure et placez l'interrupteur principal en position d'arrêt (« OFF »).
- Placez l'interrupteur mural en position d'arrêt (« OFF »).

MISE EN GARDE

- Toutes les pièces doivent être utilisées tel qu'il est indiqué dans ces instructions. Ne remplacez pas les pièces, n'en laissez pas de côté et ne les utilisez pas si elles sont usées ou brisées. Le non-respect de ces instructions peut annuler l'homologation ETL/CETL du luminaire. MISE EN GARDE Ors de la manipulation de l'appareil, ne pas appliquer de pression à la LED, tenir l'appareil par la seule base.

ADVERTENCIA

IMPORTANTE: NUNCA intente hacer trabajos sin desconectar el suministro eléctrico.

- Lea y comprenda todas las instrucciones e ilustraciones por completo antes de proceder con el ensamblaje e instalación de esta lámpara.
- Sistema está diseñado para ser instalado por un electricista calificado, de acuerdo con el código eléctrico nacional y las normas locales.
- Diríjase a la caja de fusibles o a la caja del interruptor de circuito principal en su hogar. Coloque el interruptor de alimentación principal en la posición "OFF" (APAGADO).
- Coloque el interruptor de la pared en la posición "OFF" (APAGADO).

PRECAUCIÓN

- Todas las piezas deben usarse como lo indican estas instrucciones. No reemplace las piezas, no omita piezas durante la instalación ni utilice piezas gastadas o rotas. El incumplimiento de esta indicación podría invalidar la calificación ETL/CETL esta lámpara. PRECAUCIÓN Al manipular el aparato, no aplique presión a los LED, mantenga el aparato en la base sólo.

HARDWARE

G1



Wire
Connector
Qty: 5 + 1 Extra

E1



Junction Box
Screw
Qty: 2 + 1 extra

B1



Mounting Anchor
Qty: 2 + 1 Extra

D1



Mounting
Screw
Qty: 2 + 1 Extra

H1



Set Screw
Qty: 2 + 1 Extra


WAC Lighting
www.waclighting.com
Phone (800) 526.2588 • Fax (800) 526.2585

Headquarters/Eastern Distribution Center
44 Harbor Park Drive • Port Washington, NY 11050
Phone (516) 515.5000 • Fax (516) 515.5050

Western Distribution Center
1750 Archibald Ave • Ontario, CA 91761
Phone (800) 526.2588 • Fax (800) 526.2585



FIG.1



PREPARATION

1. Shut off the power at the circuit breaker and remove existing fixture, including mounting hardware
2. Carefully unpack your new fixture and lay out all the parts on a clear area. Be careful not to lose any small parts necessary for installation.

MOUNTING THE FIXTURE (Fig. 1)

3. Thread the short stem (K1) onto the fixture top (M1).
4. Choose the stem sections (K2) needed to hang the pendant at desired height.
5. Connect the stem sections (K2) and short stem (K1) to the swivel (J1) on the canopy (I1).
6. Drill holes in the wall aligned with the keyholes located on the mounting back plate (C1). Insert the mounting anchors (BB) into the wall.

CONNECTING THE WIRES (Fig. 2)

7. Connect the transformer (A1) input wires with junction box wires as shown in Fig. 2.
8. Secure the mounting back plate (C1) to the junction box (F1) using junction box screws (E1) and fasten to the wall using the wood screws (D1). The side of the mounting back plate marked "GND" must face out.

***Requires Transformer to be recessed within the junction box!**


9. Cut fixture wires leaving at least 6" to make electrical connections. Connect two red fixture wires to one of transformer output wires. Connect two black fixture wires to other transformer output wire. Make sure that all wire connectors (G1) are secured.

Fixture and junction box ground wires should be connected to mounting plate using green screw provided. After wires are connected, tuck them carefully inside the junction box.
 10. Place the fixture's canopy (I1) over the mounting back plate (C1) and secure with screws (H1).

COMPLETING THE INSTALLATION (FIG. 3)

11. For sloped-ceiling application, rotate the wire at the top of the stem to ensure luminaire is aiming down (Fig.3).

FIG.2



**COMPATIBLE WITH THE FOLLOWING
 ELECTRONIC LOW VOLTAGE (ELV) DIMMERS**

Brand	Model
LUTRON	SELV-300P
LUTRON	DVELV-300P
LEVITON	VPE04