



KALCO
Handcrafted Since 1980

ASSEMBLY & INSTALLATION INSTRUCTIONS

MODEL: 503940

BROADWAY 3 LIGHT 19" CONVERTIBLE (PENDANT / SEMI-FLUSH)

I M A G E



If you have any questions or problems assembling your fixture please call us for assistance.

Customer Service: (702) 361-4345 or (800) 525-2655

customer.services@kalco.com

WARNING! TO REDUCE THE RISK OF FIRE OR INJURY PLEASE TAKE PRECAUTION AND FOLLOW THE STEPS BELOW.

1. If you are unfamiliar with electrical wiring, call a qualified electrician to install this unit. More than one person may be necessary to install fixture, make sure you have enough qualified help.
2. Turn off the power to the fixture's circuit at the service panel. Use a voltage detector to verify that the power is off.
3. DO NOT install bulb which exceeds the maximum wattage specified on the socket label.

Si vous avez des questions ou des problèmes assemblage de votre dispositif s'il vous plaît appel pour l'assistance.


Customer Service: (702) 361-4345 or (800) 525-2655

customer.services@kalco.com

AVERTISSEMENT! POUR RÉDUIRE LES RISQUES D'INCENDIE OU DE BLESSURES S'IL VOUS PLAÎT PRENDRE DES PRÉCAUTIONS ET SUIVEZ LES ÉTAPES CI-DESSOUS.

1. Si vous n'êtes pas familier avec le câblage électrique, appelez un électricien qualifié pour installer cet appareil. Plus d'une personne peut être nécessaire d'installer appareil, assurez vous que vous disposez de l'aide assez qualifié.
2. Coupez l'alimentation au circuit de l'appareil sur le tableau de service. Utiliser un détecteur de tension pour vérifier que l'alimentation est coupée
3. NE PAS installer l'ampoule qui excède la puissance maximale indiquée sur l'étiquette du socket.

WIRING DIAGRAM





KALCO
Handcrafted Since 1980


ASSEMBLY & INSTALLATION INSTRUCTIONS

MODEL: 503940

BROADWAY 3 LIGHT 19" CONVERTIBLE (PENDANT / SEMI-FLUSH)

KNOCK DOWN ASSEMBLY

OPTION A: PENDANT




STEP 1: Attach the fixture loop stem provided for pendant to the main fixture as shown.

STEP 2: Determine fixture height. Make adjustment if needed. Attach chain to the fixture loop and collar loop using open-able chain.

STEP 3: Secure the collar loop to canopy using collar loop ring and customized lock - up.

OPTION 2: SEMI-FLUSH



STEP 1: Attach the center stem provided for semi-flush to the main fixture and to the customized hangstraight as shown

STEP 2: Secure the hang straight to canopy using collar loop ring and customized lock - up.



KALCO
Handcrafted Since 1980

ASSEMBLY & INSTALLATION INSTRUCTIONS

MODEL: 503940

BROADWAY 3 LIGHT 19" CONVERTIBLE (PENDANT / SEMI-FLUSH)

ELECTRICAL / MOUNTING INSTALLATION



STEP 1: Fasten (2) 8-32 x 1 1/2" studs into mounting plate so that they extend away from the ceiling when the mounting plate is installed.

STEP 2: Attach mounting plate to outlet box with the (2) 8-32 x 3/4" screws.


STEP 3: Refer to wiring diagram.
With wire carefully threaded thru canopy, connect the black supply wire to the smooth fixture wire with wire connector, connect the white supply wire to the ribbed fixture wire with wire connector.

STEP 4: Carefully tuck all wires into outlet box ensuring that there are no wires pinched between the canopy and ceiling.

STEP 5: Attach the canopy to mounting plate and lock it by using two (2) pcs. of ball nut.



COMPONENTS ASSEMBLY



STEP 6: Insert the candle cover to the socket.

STEP 7: Install the bulbs, do not use bulbs that exceed 60 watts.

LIGHTING MAINTENANCE:

- Regular cleaning of fixture with proper and gentle care using a soft duster, soft lint-free or damp cloth is recommended.
- Refrain from using harsh cleaning liquids that may cause chemical reaction on the hand painted finishes.
- Always refer to the Assembly Instruction before removing any components.
- **HANDLE WITH CARE.**



KALCO
Handcrafted Since 1980

ASSEMBLY & INSTALLATION INSTRUCTIONS

MODEL: 503940

BROADWAY 3 LIGHT 19" CONVERTIBLE (PENDANT / SEMI-FLUSH)

PARTS LIST

FOR PENDANT OPTION :

IMAGE	PARTS NAME	QTY
	X2-A Parts Bag	1 PC
	Screw	2 PCS
	Ball Nut	2 PCS
	Hex Nut	2 PCS
	Stud	2 PCS
	Customized Lock-Up	1 PC
	Chain 4ft with collar loop/ring	1 PC
	Open-able chain	2 PCS
	Canopy	1 PC
	Chain Loop	1 PC
	Candle Cover	3 PCS



KALCO.
Handcrafted Since 1980


ASSEMBLY & INSTALLATION INSTRUCTIONS

MODEL: 503940

BROADWAY 3 LIGHT 19" CONVERTIBLE (PENDANT / SEMI-FLUSH)

PARTS LIST

FOR SEMI-FLUSH OPTION :

IMAGE	PARTS NAME	QTY
	X2-A Parts Bag	1 PC
	Screw	2 PCS
	Ball Nut	2 PCS
	Hex Nut	2 PCS
	Stud	2 PCS
	Customized Lock-Up	1 PC
	Canopy	1 PC
	Customized Hang straight	1 PC
	Center Stem	1 PC
	Candle Cover	3 PCS