## ASSEMBLY AND INSTALLATION INSTRUCTIONS

## P0056 / P0058 / P0060 / P0062

WARNING: BE SURE TO SHUT OFF POWER AT THE MAIN FUSE OR CIRCUIT BREAKER BOX BEFORE INSTALLING OR SERVICING THIS FIXTURE.

NOTE: 1. Before installing, consult local electrical codes for wiring and grounding requirements. 2. READ AND SAVE THESE INSTRUCTIONS.



130709

- 1. Carefully unpack the fixture, lay out the fixture on a clean surface.
- 2. Use suitable tools to unscrews the hex nuts from the canopy, remove the nipple-1, metal pad and finial from the canopy. Save the finial. (See Fig.1)
- 3. Unscrew the finial and remove the coupling and collar.
- 4. Attach the nipple to the coupling.
- 5. Attach the nipple to the mounting strap, then secure it with a washer and hex nut.
- 6. Attach the mounting strap to the outlet box by using two mounting screws.
- 7. Install the Fixture. (the Fixture is sold separately)
  - a. Remove the canopy or coupling from the fixture before installation (See Fig.2 ~ 5)
  - b. **Side fixture :** Thread the fixture wire through the canopy as showed, and then secure the fixture to the canopy with metal pad, washer and hex nut.
  - c. Center Fixture: Thread the fixture wire through the collar and canopy. Slip the collar, canopy until they rest on top of the fixture. Next, connect the fixture to coupling.
- Cut any excess fixture wires leaving only about 8" (20cm) length from the top end of nipple-1, then strip off 3/4"the fixture wires of plastic from each end.
- 9. Pull out the outlet wires and house grounding wire from the outlet box. Make wire connections using the wire nuts:
  - ---All black wires from rods to the black wire from power source.
  - ---All white wires from rods to the white wire from power source.
  - ---Attach the grounding wire to the mounting strap with the green grounding screw. Then connect it to the house grounding wire and all grounding wires from the frame with a wire nut.

Carefully put the wires back into the outlet box.

- 10. Attach the canopy to the mounting strap by inserting the coupling, then secure it with the collar.
- 11. Angled mounting recommended for a vaulted or angled ceiling. (See Fig. 6~8)







A: 12-3/4" B: 2-3/8"

