

One-Light Outdoor

Project:

Fixture Type: Location:

Contact:

Wall mounted • Wet location listed PROGRESS LED



Description:

Arrive LED lanterns feature a die-cast aluminum, powder coated frame and heavily textured glass. One-light small wall lantern. 90+ CRI, 3000K, 623 lumens (source). Energy Star.

Specifications:

- Black (-31) (painted)
- · Die-cast aluminum Construction
- Clear Seeded glass panels
- LED Module is replaceable (part # 93054049)
- Die-cast aluminum, powder coated frame.
- Heavily textured glass.
- 90+ CRI, 3000K, 623 lumens. Energy Star.
- 623 lumens 69.2 lumens/watt per module (source)
- 3000K color temperature, 90+ CRI.
- Dimmable to 10% brightness (See Dimming Notes)
- Back plate covers a standard 4" octagonal recessed outlet box
- Mounting strap for outlet box included
- 6" of wire supplied
- ENERGY STAR® qualified
- · Meets California Title 24 high efficacy requirements for outdoor use only

Performance:

Number of Modules	1	
Input Power	9w	V
Input Voltage	120 V	D H H G W
Input Frequency	60 Hz	
Lumens/LPW (Source)	623/69.2 (LM-82)	
Lumens/LPW (Delivered)	396/49.5 (LM-79)	
ССТ	3000 K	
CRI	90 CRI	
Life (hours)	60,000 (L70/TM-21)	ł
FCC	Meets FCC Title 47, Part 15 Class B	
Min. Start Temp	-30 °C	
Max. Operating Temp	30 °C	
Warranty	5 year warranty	
Labels	cCSAus Wet location listed	
	ENERGY STAR [®] qualified	
	Meets California Title 24 high efficacy requirements	
	for outdoor use only	

P6067-3130K9

Images:



Dimensions:

Width: 6" Depth: 7-3/8" Height: 8-3/4" H/CTR: 4"

Glass Width: 0-1/8" Length: 3-3/4" Height: 6-1/16"



One-Light Outdoor

Wall mounted • Wet location listed PROGRESS LED



P6067-3130K9

Dimming Notes:

P6067 is designed to be compatible with many ELV/Reverse Phase controls.

The following is a partial list of known compatible dimmer controls.

Dimming Controls

Lutron Nova T NTELV-300

Lutron Vierti VTELV-600

Lutron Ariadni AYCL-153P

Lutron Diva DVCL-153P

Lutron Maestro MAELV-600

Lutron spacer/system SPSELV-600

Leviton Renoir II AWRMG-EAW

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.