# INSTALLATION INSTRUCTION 808 Low Voltage LED Track Luminaires

HHT-808LED, LHT-808LED, JHT-808LED

## CAUTION:

Read all instructions before installing. Switch off power before installing or re-lamping. Do not attempt to energize anything other than a track light fixture. All installation shall be in accordance with NEC and all local codes

#### **OVERVIEW:**

Fixtures are designed for use on on WAC "L", "H", "J" series track. They may also be used on other manufacturer's brand of track (consult factory for compatibility).

#### LAMPING:

- 1. Use dimmable MR16 LED lamp (included)
- 2. Remove the check ring.
- 3. Insert the MR16 lamp by aligning the pins with the holes in the ceramic socket, and pushing straight in.
- 4. Re-install the check ring.

### **FIXTURE INSTALLATION**

- 1. Note the track has a groove running its length to indicate polarity.
- 2. Note the slant of the locking tab.
- 3. Insert adapter into track slot and rotate adaptor 90° so that the low side of the locking tab faces the grooved side of the track.
- 4. Make sure the locking tab seats in the track slot.
- 5. Removal is the reverse procedure. Track heads may be positioned anywhere along the track length.
- 6. Not suitable for use on wall mounted track.



Responsible Lighting®







Headquarters/Eastern Distribution Center 44 Harbor Park Drive • Port Washington, NY 11050 Phone (516) 515.5000 • Fax (516) 515.5050