# **M** WARNINGS AND CAUTIONS

- $\cdot$  Make sure  $\ensuremath{\text{POWER}}$  is  $\ensuremath{\text{COMPLETELY OFF}}$  at the fuse box
- $\cdot$  Have your fixture installed by a qualified licensed electrician
- $\cdot$  Prepare everything in a clear area
- Wear gloves at all times during this installation
   Read instructions carefully before you start assembly
- $\cdot$  Keep this installation sheet for future reference

Please Note:

- · This Alora Mood LED fixture comes with pre-wired LED module(s)
- $\cdot$  Unless instructed, Do Not touch any part of the LED module(s) as any unnecessary contact with the module could cause permanent damage
- · For dimming, an ELV (Electronic Low Voltage) type of dimmer is required
- · 120V input

## NOTICE

- The important safeguards and instructions outlined in this sheet cannot cover all possible conditions and situations that may occur. It must be understood that caution and certain care factors must be followed. These instructions are provided for your safety and we highly recommend that a licensed, trained electrician install this unit.
- This fixture is designed to be mounted on a correctly installed standard round or octagon box OR through a wiring box with a plaster frame. The box must be securely mounted to the structure of the building. The crossbar and hardware supplied should be used, directly mounting the fixture to the outlet box may make it impossible to correctly align the fixture.

### ASSEMBLY INSTRUCTIONS

#### Step 1

Remove fixture from its original package.

#### Step 2

Attach crossbar (1c) to electrical junction box (1a) using junction box screws provided (1e) in hardware package.

#### Step 3

Make proper electrical connections (**black** to **hot** "L", **white** to **neutral** "N", **ground** to **"GND"**) with wire nuts (1b) provided in hardware package.

#### Step 4

Install Pan-Head Crossbar Mounting Screws (1d) halfway into threaded holes on crossbar (1c). Align keyholes on fixture (2a) and module to Pan-Head Crossbar Mounting Screws (1d) heads, insert and turn, and then secure with screw driver.

#### Step 5

Twist acrylic cover (3a) onto fixture (2a) to secure.

You are now ready to enjoy your fixture.



# alora mood

P. 1.855.855.8926
CANADA: 19054 28th Ave., - Surrey, BC V3Z 6M3
USA: 3035 E. Lone Mountain Rd. - Las Vegas, NV 89081
www.aloramood.com
20230526