

## **Step by Step Assembly Instructions:**

## \*Safety Precautions:

- 1. Turn off the power at the main electrical service box before starting installation.
- 2. Electrical connections must comply with local code ordinances or national electrical codes.

## **Installation Steps:**

- 1. Connect the chain to the fixture loop and feed the wires through the chain to your desired length.
  - A general rule is the bottom of the fixture should be 30 inches from a tabletop or 9 feet from the floor for a foyer fixture.
- 2. Feed wires through upper connector loop and nut leaving 12-15' of extra wire for future height adjustments.
- 3. Unscrew the upper connector loop nut and slide down chain.
- 4. Slip canopy over wires, upper connector loop and slide down chain.
- 5. Attach mounting bracket to upper connector loop using threaded pipe and nuts provided.
- 6. Ensure the electrical box in the ceiling can carry the weight of your fixture. It may need extra support. If you are unsure, please contact a qualified electrician. If the box is secure, please proceed by attaching the mounting bracket to the electrical box using the crews provided.
- 7. Connect the ground wire to the electrical box. Connect the white wire from the ceiling to the identified conductor. Connect the black wire from the ceiling to the non-identified conductor from the chandelier.
- 8. Slide canopy and upper loop nut up the chain to cover the electrical box ensuring all wires are tucked inside and not pinched between canopy and ceiling.
- 9. Secure the canopy using the upper connector loop nut.
- 10. Install glass and secure it with screws
- 11. Install proper type wattage of bulb as per label on socket or socket ring.

