

# ASSEMBLY INSTRUCTIONS

MODEL : E20902-10

**NOTE:** Only the technical personnel can be allow to fix and maintain.

## IMPORTANT!

Make sure that the power is switch off at the electricity mains supply before commencing work.

## FIXING INSTRUCTIONS

1. Remove the mounting plate (C) from the fitting.
2. Carefully mark holes on the wall for fixing. Take care when drilling holes that the drill does not damage the mains supply wires. Screw the mounting plate to the wall using the wood screws.
3. a. Mount ground wire on mounting plate (C) onto ground screw (E) in the junction box (A).  
Firmly connect the mains supply wires to the light fitting using the connectors provided (B).  
Ensure that wires are secure and that no bare wire is exposed.  
b. Mount the mounting plate (C) to the junction box (A) using the screws.  
c. Mount the fitting to the mounting plate (C), tighten it using the securing screws (D).
4. Turn on the power, enjoy your new lighting product.

## REPLACEMENT BULB

Do not exceed the maximum wattage.

Light bulbs recommended:

E20902-10 - 2 x Max. 1W LED

## CLEANING CARE

Clean with a soft dry cloth.

## SAFETY INFORMATION

1. Do not touch the bulb with bare hands. Always switch off the electricity supply and allow to cool for 10 minutes before changing the light bulbs.
2. (F) Please change the tranformer in time if it's failed. (F) Please loosen the screw, connect the cable correctly after take off the cover of transformer. Then lock the cover tightly .

